

SPECIFICATION

TO ALL WHOM IT MAY CONCERN:

BE IT KNOWN THAT I, MAKOTO MATSUSHIMA, a citizen of Japan residing at Hyogo, Japan have invented certain new and useful improvements in

PULSE WIDTH MODULATION SIGNAL GENERATING CIRCUIT

of which the following is a specification:-

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention generally relates to pulse width modulation signal generating circuits and, more particularly, to a pulse width modulation signal generating circuit which generates a pulse width modulation signal supplied to a light-emitting device such as a light-emitting diode to cause the light-emitting device to emit a light.

10 2. Description of the Related Art

FIG. 1A is a block diagram showing a structure of a portable telephone A2 provided with a luminescence circuit C4 of a light-emitting diode 102, which uses a conventional pulse width modulation (PWM) signal generating circuit 200. The portable telephone A2 comprises, in addition to the luminescent circuit C4, a central processing unit (CPU) 150, a read only memory (ROM) 151 which stores a control program of the luminescent circuit C4, a random access memory (RAM) 152 which is used as a work memory when executing each program, a transmission and reception part 153 and an operation part 154 including a liquid crystal panel, a ten-key, a microphone and a speaker.

The CPU 150 controls the light-emitting diode 102, which is an incoming call lamp, provided in the

luminescence circuit C4 to emit a wavy light at a time of reception of a telephone call signal from a remote terminal. Here, the emission of a wavy light refers to a light-emitting method in which an intensity of light
5 is increased and decreased gradually in a wavelike manner.

Specifically, the CPU 150 outputs a 4-bit digital signal increasing and decreasing with a predetermined cycle to the luminescence circuit C4. A
10 PWM signal generating circuit 200, which constitutes the luminescence circuit C4, applies a PWM signal determined according to a value of the digital signal output from the CPU 150 to a gate of an N-channel type MOSFET 101. When the PWM signal supplied is active, i.e., at a high
15 level in the luminescence circuit C4, the MOSFET 101 turns on so as to cause the light-emitting diode 102, to which a power supply voltage V_{cc} is supplied, to emit a light.

A digital-to-analog converter (DAC) 201
20 provided in the PWM signal generating circuit 200 is driven by a voltage of 3V, a voltage of 2V being input as a top voltage VRT and a voltage of 1V being input as a bottom voltage VRB. The DAC 201 outputs an analog signal V_a (1V-2V) corresponding to the value (0000-1111)
25 of the 4-bit digital signal supplied from the CPU 150 of

the portable telephone, as shown in FIG. 1B. A triangular-wave generator 202 outputs a triangular wave TW of a predetermined frequency. As shown in FIG. 1C, a comparator 203 outputs the PWM signal of a high level or
5 a low level according to the sign (positive or negative) of the difference that is obtained by subtracting the analog signal Va output from the DAC 201 from the triangular-wave signal TW output from the triangular-wave generator 202.

10 It should be noted that the luminescence circuit C4 mentioned above does not relate to an invention which has become publicly known.

 In the luminescence circuit C4 having the above-mentioned structure, in order to cause the light-
15 emitting diode 102 to emit a wavy light, that is, in order to gradually turn on and turn off the light-emitting diode 102 within a period T, the CPU 150 is required to execute a control program to gradually increase the value of the 4-bit digital signal within
20 one half ($T/2$) of the period T and then gradually decrease the digital signal within another half ($T/2$) of the period T. In this case, the CPU 150 is required to execute the above-mentioned control program parallel to other processes such as an incoming call reception
25 processes (a display control of a liquid crystal panel

constituting the operation part 154), thereby increasing a load to the CPU 150. For this reason, in order to achieve a smooth incoming call reception process, a CPU is required which can operate at a higher speed but more
5 expensive than a CPU of a portable telephone provided with a luminescence circuit which does not cause a light-emitting diode to emit the above mentioned wavy light.

In the PWM signal generating circuit 200 used
10 in the above-mentioned luminescence circuit C4, even when there is no arrival of an incoming call and there is no need to cause the light-emitting diode 102 to emit a light, an electric power of the voltage of 3V is consumed unless a power supply is turned due to an
15 energy saving function, etc. Moreover, since there is a part which processes an analog signal in the circuit, a fluctuation tends to be generated in the output PWM signal.

20 SUMMARY OF THE INVENTION

It is a general object of the present invention to provide an improved and useful PWM signal generating circuit in which the above-mentioned problems are eliminated.

25 A more specific object of the present

invention is to provide a PWM signal generating circuit which outputs a stable PWM signal for increasing and decreasing a duty ratio at a predetermined rate within a predetermined period without requiring an improvement of
5 a process capacity of a CPU as compared to a conventional PWM signal generating circuit.

In order to achieve the above-mentioned objects, there is provided according to the present invention a PWM signal generating circuit comprising: a
10 first counter circuit periodically changing a PWM signal output therefrom into an active state; and a second counter circuit changing the PWM signal, which has been changed into the active state by the first counter circuit, into an inactive state within each cycle,
15 wherein the second counter circuit increases and decreases an active-to-inactive time period from a time when the PWM signal is changed into the active state to a time when the PWM signal is changed into the inactive state.

20 The PWM signal generating circuit according to the present invention may consist of a plurality of circuit elements each of which outputs a digital signal.

The PWM signal generating circuit according to the present invention may further comprise a first
25 specifying circuit that specifies an upper limit value

and a lower limit value, wherein the second counter circuit may change the active-to-inactive time period periodically within a range between the upper limit value and the lower limit value.

5 Additionally, the PWM signal generating circuit according to the present invention may further comprise a second specifying circuit that specifies a first schedule time and a second schedule time, wherein the second counter circuit may start to decrease the
10 active-to-inactive time period after the active-to-inactive time period reaches the upper limit value and the first schedule time has elapsed, and the second counter circuit may increase the active-to-inactive time
15 the lower limit value and the second schedule time has elapsed.

 The PWM signal generating circuit according to the present invention can smoothly increase and decrease a duty ratio of the PWM signal only by being supplied
20 with a reference clock signal after the operation parameters are set. Thereby, the load to a CPU which controls the PWM signal generating circuit is reduced. Moreover, if the PWM signal generating circuit according to the present invention is constituted by only circuit
25 elements each of which outputs a digital signal, a more

stable operation can be achieved than a case where a luminescence time is adjusted using circuit elements outputting analog signals such as an analog-to-digital converter (DAC).

5 Moreover, since an electric power is consumed by operation only at a reception time, a power consumption is much less than that in a case where a DAC is used which consumes an electric power at a time other than a reception time, unless a power is turned off due
10 to an energy saving function, etc., thereby suitable for an application such as a portable telephone which is driven by a battery.

 Other objects, features and advantages of the present invention will become more apparent from the
15 following detailed description when read in conjunction with the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

 FIG. 1A is a block diagram of a portable
20 telephone provided with a luminescence circuit of a light-emitting diode, which uses a conventional pulse width modulation signal generating circuit;

 FIG. 1B is an illustration for explaining a digital-to-analog conversion performed by a digital-to-
25 analog converter shown in FIG. 1A;

FIG. 1C is an illustration for explaining a generation of a PWM signal generated by a comparator shown in FIG. 1A;

FIG. 2 is a block diagram of a portable
5 telephone provided with a luminescence circuit using a PWM signal generating circuit according to an embodiment of the present invention;

FIG. 3 is a block diagram of a structure of the PWM signal generating circuit;

10 FIG. 4 is a circuit diagram of a 4-bit counter section shown in FIG. 3;

FIG. 5 is a circuit diagram of an 8-bit counter section shown in FIG. 3;

15 FIG. 6 is a circuit diagram of a 4-bit register section shown in FIG. 3;

FIG. 7 is a time chart showing a status of each signal in the PWM signal generating circuit shown in FIG. 2 in a case in which a gradient setting value is set to "00000100";

20 FIG. 8 is a time chart showing a status of each signal in the PWM signal generating circuit shown in FIG. 2 in a case in which the gradient setting value is set to "00011000";

25 FIG. 9 is a graph showing changes in a luminescence time per 1 cycle of a 4-bit counter

specified by a PWM signal output by the PWM signal generating circuit shown in FIG. 2 which operates in the state shown in FIG. 7; and

FIG. 10 is a graph showing changes in the luminescence time LT per 1 cycle of the 4-bit counter specified by the PWM signal output by the PWM generating circuit shown in FIG. 2 which operates in the state shown in FIG. 8.

10 DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

A description will now be given, with reference to the drawings, of an embodiment of the present invention. FIG. 2 is a block diagram of a portable telephone A1 provided with a luminescence circuit C1 using a PWM signal generating circuit 100 according to an embodiment of the present invention.

The portable telephone A1 comprises, in addition to the above-mentioned luminescence circuit C1, a central processing unit (CPU) 150, a read only memory (ROM) 151 which stores programs executed when an incoming call is detected, a random access memory (RAM) 152 which is used as a work memory when executing each program, a transmission and reception part 153 and an operation part 154 including a liquid crystal panel, a ten-key, a microphone and a speaker. It should be noted

that the same reference numerals are given to parts equivalent to the parts of the portable telephone A2 shown in FIG. 1A.

The luminescence circuit C1 controls an
5 intensity of a light emitted from the light-emitting diode 102 to increase and decrease at a predetermined cycle only by specifying necessary operation parameters (a gradient setting value, an upper limit value, a lower limit value, a first target value and a second target
10 value) without a digital signal, which increases and decreases at the predetermined cycle, being output from the CPU 150. The designation of the above-mentioned operation parameters is not limited to a method in which the operation parameters are set by an external source
15 such as the CPU 150, and the operation parameters may be set to their target values in the luminescence circuit C1.

Specifically, the CPU 150 outputs, as
operation parameters, information regarding a gradient
20 setting value, upper and lower limit values and first and second schedule values. The gradient setting value (8-bit data) is for setting a degree of a smooth turn-on and turn-off of the light-emitting diode 102. The upper and lower limits are for the luminescence duty ratio of
25 the light-emitting diode 102. The first and second

schedule values are for setting time periods (first and second schedule time) after the luminescence duty ratio of the light-emitting diode 102 becomes the maximum or minimum value until the luminescence duty ratio is

5 started to be decreased or increase, respectively. The CPU 150 also outputs a reference clock signal CLK. The reference clock signal CLK may be generated by an external circuit other than the luminescence circuit C1 or the CPU 150.

10 The luminescence circuit C1 comprises: a PWM signal generating circuit 100 according to the embodiment of the present invention; an N-channel type MOSFET 101 having a gate which receives the PWM signal output from the PWM signal generating circuit 100; and a
15 light-emitting diode 102 connected between a drain electrode of the FET 101 and a power supply voltage Vcc. When the PWM signal output from the PWM signal generating signal in the luminescence circuit C1 is active, that is, at a high level, the FET 101 turns on
20 and the light-emitting diode 102 emits a light. On the other hand, when the PWM signal is the inactive, that is, at a low level, the FET 101 turns off, thereby turning off the light-emitting diode 102.

 The PWM signal generating circuit 100
25 increases the luminescence duty ratio of the light-

emitting diode 102 to an upper limit value at a speed
(tempo or rhythm) corresponding to the value of the
gradient setting value. When the luminescence duty
ratio of the light-emitting diode 102 reaches the upper
5 limit value, the luminescence duty ratio is maintained
at the upper limit valued for a time period (the first
schedule time) until a counter 4f mentioned later counts
up the first schedule value. Thereafter, the
luminescence duty ratio is decreased at a speed
10 determined by the above-mentioned gradient setting value
until the luminescence duty ratio of the light-emitting
diode 102 reaches the lower limit value. When the
luminescence duty ratio of the light-emitting diode 102
reaches the lower limit value, the luminescence duty
15 ratio is maintained at the lower limit valued for a time
period (the second schedule time) until a counter 4i
mentioned later counts up the second schedule value.
Thereafter, the PWM signal generating circuit 100 again
increases the luminescence duty ratio of the light-
20 emitting diode 102 to the upper limit value at a speed
(tempo or rhythm) corresponding to the value of the
gradient setting value so as to continue the above-
mentioned control of the luminescence duty ratio of the
light-emitting diode 102.

25 FIG. 3 is a block diagram showing a structure

of the PWM signal generating circuit 100. The PWM signal generating circuit is constituted by only circuit elements outputting digital signals, and comprises a first counter circuit C2 and a second counter circuit C3.

5 The first counter circuit C2 changes the output PWM signal to be active periodically. The second counter circuit C3 changes the PWM signal to be inactive within each period, and increases and decreases a time period from a time when the PWM signal is changed to be active
10 (at a high level in this circuit) until a time when the PWM signal is changed to be inactive (at a low level in this circuit).

A 4-bit counter section 1 operates in synchronization with a reference clock signal CLK so as
15 to output a high-level pulsed set signal (1-bit data) when starting a count and also output a count value (4-bit data) at an appropriate time. An 8-bit counter section 2 operates based on the reference clock signal CLK so as to output a high-level pulsed trigger signal
20 (1-bit data) when the count value (8-bit data) matches a gradient setting value (8-bit data) supplied by the CPU 150 and also reset the count value. A 4-bit up-down counter 3 performs a counting operation according to the input of the high-level pulsed trigger signal (1-bit
25 data) output from the 8-bit counter section 2. The 4-

bit up-down counter 3 functions as an up-counter when an up-down control signal is at a high level, and also functions as a down-counter when the up-down control signal is at a low level.

5 The 4-bit register section 4 holds the count value (4-bit data) which the 4-bit up-down counter 3 outputs at the time of input of the set signal from the 4-bit counter section 1, and outputs the count value to a comparator 5 of the subsequent stage. When the count
10 value (4-bit data) of the counter 3 concerned becomes equal to a predetermined maximum value (4-bit data) while the counter 3 is functioning as an up-counter, the 4-bit register section 4 does not update the value currently held even if it receives the set signal, and,
15 thereafter, outputs the count value which corresponds to the maximum value for a period of time (first schedule period) during which a first built-in counter (corresponding to a counter 4f shown in FIG. 5), which starts at a time when the above-mentioned count value
20 becomes equal to the maximum value, counts a first schedule value. Moreover, when the count value (4-bit data) of the first built-in counter turns into the first schedule value (4-bit data), the 4-bit register section 4 changes the up-down control signal being output to the
25 4-bit up-down counter 3 to a low level, and updates the

held count value to the count value being output by the counter 3 in response to the input of the set signal.

On the other hand, when the count value (4-bit data) of the counter 3 concerned becomes equal to a
5 predetermined minimum value (4-bit data) while the counter 3 is functioning as a down-counter, the 4-bit register section 4 does not update the value currently held even if it receives the set signal, and, thereafter, outputs the count value which corresponds to the minimum
10 value for a period of time (second schedule period) during which a second built-in counter (corresponding to a counter 4i shown in FIG. 5), which starts at a time when the above-mentioned count value becomes equal to the minimum value, counts a second schedule value.
15 Moreover, when the count value (4-bit data) of the second built-in counter turns into the second schedule value (4-bit data), the 4-bit register section 4 changes the up-down control signal being output to the 4-bit up-down counter 3 to a high level, and updates the held
20 count value to the count value being output by the counter 3 in response to the input of the set signal.

The comparator 5 outputs a reset signal of a high level to a flip-flop 6 when the count value output from the 4-bit counter section 1 becomes larger than the
25 count value output from the 4-bit register section 4.

The flip-flop 6 starts output of the PWM signal, which is a diode luminescence signal, in response to the input of the high-level set signal from the 4-bit counter section 1, and returns the PWM signal to a low level in response to the high-level reset signal from the comparator 5 so as to ends the luminescence.

FIG. 4 is a circuit diagram of the 4-bit counter section 1 shown in FIG. 3. The reference clock signal CLK is supplied to a 4-bit counter 1a. An output terminal (a bus which outputs 4-bit data) of the 4-bit counter 1a is connected to one of signal input terminals of a 2-input NOR gate 1b, and also connected to a signal input terminal of the 4-bit register section 4. The remaining signal input terminal of the NOR gate 1b is grounded, and is always supplied with a low level 4-bit signal "0000".

It should be noted that the NOR gate 1b acquires the negative OR of two sets of 4-bit data, and outputs a high-level set signal (1-bit data) only when both the two sets of 4-bit data supplied are "0000". That is, more specifically, the 2-input NOR gate 1b comprises: a 2-input NOR gate having two signal input terminals, data of a least significant bit from among 4-bit data output by the 4-bit counter 1a being supplied

to one of the signal input terminals and "0" data being supplied to the remaining signal input terminal; a 2-input NOR gate having two signal input terminals, data of a second least significant bit being supplied to one
5 of the signal input terminals and "0" data being supplied to the remaining signal input terminal; a 2-input NOR gate having two signal input terminals, data of a third least significant bit being supplied to one of the signal input terminals and "0" data being
10 supplied to the remaining signal input terminal; a 2-input NOR gate having two signal input terminals, data of a most significant bit being supplied to one of the signal input terminals and "0" data being supplied to the remaining signal input terminal; and a 4-input AND
15 gate to which output of those four NOR gates are supplied.

Similarly, in the circuit explained below, the logical gates having input terminals, to which a bus line is connected, comprise identical logical gates of a
20 number the same as the number of bits of data flowing through the bus and an AND gate performing all ANDs of the outputs of those logical gates. The logical gates are supplied with sets of data corresponding to the respective bits (which means sets of data of least
25 significant bits, sets of data of second least

significant bits, ...). It should be noted the logical gates explained below are an AND gate 2b shown in FIG. 5 and AND gates 4j and 4g shown in FIG. 6.

FIG. 5 is a circuit diagram of the 8-bit counter section 2 shown in FIG. 3. The reference clock signal CLK is supplied to an 8-bit counter 2a. An output of the 8-bit counter 2a is connected to the signal input terminal of the 2-input AND gate 2b. A gradient setting value which is 8-bit data is supplied to the remaining signal input terminal of the AND gate 2b. The AND gate 2b outputs a high-level reset signal (1-bit data) when the sets of the 8-bit data supplied thereto completely match each other. As mentioned above, the AND gate 2b comprises eight AND gates to which sets of data of each corresponding bit is supplied and an 8-input and 1-output AND gate to which outputs of the eight AND gates are supplied.

The output terminal of the AND gate 2b is connected to a clock signal input terminal of the 4-bit up-and-down counter 3, and also connected to a reset signal input terminal of the 8-bit counter 2a. When the count value output from the counter 2a matches the gradient setting value, the output of the AND gate 2b is changed into a high level. Accordingly, the 8-bit counter 2a is reset, and the output signal of the AND

gate 2b returns to a low level.

FIG. 6 is a circuit diagram of the 4-bit register section 4 shown in FIG. 3. An output signal (4-bit data) of a 4-bit up-down counter 3 is supplied to a negative signal input terminal of a comparator 4b, a positive signal input terminal of a comparator 4c and a data input terminal of a register 4e. The 4-bit data representing an upper limit value is supplied to a positive signal input terminal of the comparator 4b.

10 The comparator 4b outputs a high-level comparison result signal (1-bit data) while the output of the 4-bit up-down counter 3 is equal to or smaller than the upper limit value. On the other hand, the 4-bit data representing an lower limit value is supplied to a negative signal input terminal of the comparator 4c.

15 The comparator 4c outputs a high-level comparison result signal (1-bit data) while the output of the 4-bit up-down counter 3 is equal to or greater than the lower limit value.

20 The set signal (1-bit data) of the 4-bit counter section 1 is supplied to one of signal input terminals of the 2-input AND gate 4a. The remaining signal input terminal of the AND gate 4a is connected to an output terminal of the 2-input AND gate 4d. A signal

25 output terminal of the comparator 4b is connected one of

signal input terminals of the 2-input AND gate 4d, and also connected to an enable terminal E of a counter 4f. Additionally, a signal output terminal of the comparator 4c is connected to the remaining signal input terminal
5 of the AND gate 4d, and also connected to an enable terminal E of a counter 4i.

In the above-mentioned structure, the AND gate 4d outputs a high-level signal when the count value output by the 4-bit up-down counter 3 is between the
10 upper limit value and the lower limit value. On the other hand, the AND gate 4d outputs a low-level signal when the count value of the 4-bit up-down counter 3 is greater than the upper limit value or smaller than the lower limit value. When the AND gate 4d is outputting
15 the high-level signal, the AND gate 4a outputs a high-level signal to the enable terminal E of the register 4e in response to an input of the set signal of the 4-bit counter section 1. When receiving the above-mentioned high-level signal at the enable terminal E, the register
20 4e holds the count value supplied from the signal input terminal, and outputs the held data to a comparator 5.

When the AND gate 4d is outputting the low-level signal, i.e., when the count value which the 4-bit up-down counter 3 outputs becomes greater than the upper
25 limit value or smaller than the lower limit value, the

AND gate 4a continuously outputs a low-level signal irrespective of the set signal from the 4-bit counter section 1. According to the above-mentioned structure, the data held in the register 4e is not updated after
5 the count value becomes greater than the upper limit value or becomes smaller than the lower limit value.

The counter 4f starts a counting operation when the count value which the counter 3 outputs exceeds the upper limit value, that is, when the high-level
10 signal is supplied to the enable terminal E from the comparator 4b, and outputs the count value to one of signal input terminals of a 2-input AND gate 4g. The first schedule value is supplied to the remaining signal input terminal of the AND gate 4g. The AND gate 4g
15 outputs a high-level signal to a set terminal of a flip-flop 4h of the subsequent stage when the count value of the counter 4f becomes equal to the first schedule value. Accordingly, an output inversion signal of the flip-flop 4h is supplied to the up-down control signal input
20 terminal of the 4-bit up-down counter 3. Thus, the counter 3, which has been functioned as an up-counter, is changed to function as a down-counter.

Similarly, the counter 4i starts a counting operation when the count value which the counter 3
25 outputs becomes smaller than the lower limit value, that

is, when the high-level signal is supplied to the enable terminal E from the comparator 4c, and outputs the count value to one of signal input terminals of a 2-input AND gate 4j. The second schedule value is supplied to the remaining signal input terminal of the AND gate 4j. The AND gate 4j outputs a high-level signal to a reset terminal of the flip-flop 4h of the subsequent stage when the count value of the counter 4i becomes equal to the second schedule value. According to the above-mentioned structure, a high-level output inversion signal is output from the flip-flop 4h to the up-down control signal input terminal of the 4-bit up-down counter 3. Thus, the counter 3, which has been functioned as a down-counter, is changed to function as an up-counter.

FIG. 7 is a time chart showing a status of each signal in the PWM signal generating circuit 100 in a case in which the gradient setting value is set to "00000100", that is, in a case in which an increasing rate of a luminescence duty ratio of the light-emitting diode specified by the gradient setting value is set a relatively fast tempo. FIG. 8 is a time chart showing a status of each signal in the PWM signal generating circuit 100 in a case in which the gradient setting value is set to "00011000", that is, in a case in which

an increasing rate of the luminescence duty ratio of the light-emitting diode specified by the gradient setting value is set to a relatively slow tempo.

As apparent from comparison between FIG. 7 and
5 FIG. 8, by changing the gradient setting value, a rate of increase and decrease of a period, during which the PWM signal is at a high level within a cycle in which the set signal is output.

Moreover, as shown in FIG. 7 and FIG. 8, the
10 flip-flop 6 changes a signal level of the PWM signal to a high level in response to an input of the high-level pulsed set signal output from the 4-bit counter section 1. As shown in FIG. 2, in response to the input of the high-level PWM signal, the N-channel type MOSFET 101
15 turns on, as shown in FIG. 2, and, thereby, the light-emitting diode 102 emits a light. Moreover, the 4-bit register section 4 holds the count value output from the 4-bit up-down counter 3.

FIG. 7 shows that "0100" is held according to
20 the first input of the set signal. Additionally, FIG. 7 shows that "0111" is held according to a next input of the set signal.

Moreover, FIG. 8 shows that "0000" is held according to the first input of the set signal.
25 Additionally, FIG. 8 shows that "0001" is held according

to a next input of the set signal. The 4-bit register section 4 returns the PWM signal to a low level after the count value output by the 4-bit counter section 1 becomes equal to the held count value.

5 FIG. 9 is a graph showing changes in the luminescence time LT per 1 cycle of the 4-bit counter 1 specified by the PWM signal output by the PWM signal generating circuit 100 which operates in the state shown in FIG. 7. In this example, the upper limit value is
10 represented by LTa and the lower limit value is represented by LTb. Additionally, the first schedule value is set to a count value corresponding to a time period t1, and the second schedule value is set to a count value corresponding to a time period t2.

15 FIG. 10 is a graph showing changes in the luminescence time LT per 1 cycle of the 4-bit counter 1 specified by the PWM signal output by the PWM generating circuit 100 which operates in the state shown in FIG. 8. In this example, the upper limit value is represented by
20 LTc and the lower limit value is represented by LTd. Additionally, the first schedule value is set to a count value corresponding to a time period t3, and the second schedule value is set to a count value corresponding to a time period t4.

25 It can be interpreted from comparison between

FIG. 9 and FIG. 10, by increasing the gradient setting value, an inclination θ_2 can be made smaller than an inclination θ_1 that represents an amount of change in the luminescence time LT per unit time.

5 As mentioned above, by using the PWM generating circuit 100 having the above-mentioned structure and after setting the gradient setting value, the upper limit value, the lower limit value, the first schedule value and the second schedule value, the
10 luminescence time of the light-emitting diode 102 can be increased and decreased smoothly with a desired tempo and a desired width of change (corresponding to difference between the upper limit value and the lower limit value) during a predetermined time period (per 1
15 cycle of the 4-bit counter) only by supplying the reference clock signal CLK without any load to the CPU
150.

 Moreover, by constituting the PWM generating circuit 100 only by circuit elements outputting digital
20 signals, a more stable operation can be achieved than a case in which a luminescence time is adjusted using circuit elements outputting analog signals such as a DAC. Moreover, since an electric power is consumed by
operation only at a reception time, a power consumption
25 is much less than that in a case where a DAC is used

which consumes an electric power at a time other than a reception time, unless a power is turned off due to an energy saving function, etc., thereby suitable for an application such as a portable telephone which is driven
5 by a battery.

Furthermore, a further complicated turning on and off of the light-emitting diode can be easily achieved by merely changing the gradient setting value, the upper limit value, the lower limit value, the first
10 schedule value and the second schedule value by a control of the CPU 150.

The present invention is not limited to the specifically disclosed embodiments, and variations and modifications may be made without departing from the
15 scope of the present invention.

The present application is based on Japanese priority application No. 2002-338129 filed November 21, 2002, the entire contents of which are hereby
incorporated by reference.

20

25